O ICOM

COM

IC-A16

ENT_{SET} 0121.5

g 16E

IC-A16E

VHF AIR BAND TRANSCEIVER

8.33/25 kHz Ground to Air Radio with **Class Leading 1500 mW Powerful Audio**

- 8.33 kHz and 25 kHz channel spacing
- 1500 mW loud audio provides clear communications
- 6 W (PEP) /1.8 W (carrier) RF output power

Built-in Bluetooth® for Hands-Free Operation* * Bluetooth operation depending on the transceiver version.

🚯 Bluetooth®

Large capacity battery pack provides 17 hours* of long battery life With BP-280. Typical operation with TX : RX : Standby = 5:5:90. (Bluetooth OFF, backlight OFF)

Compact, waterproof durable body (IP67/54 and MIL-STD-810-G)

LCD and key backlight for night time operation

Compatible* with third-party aviation headsets * Optional headset adapter OPC-2401 required.

And More

- Auto Noise Limiter (ANL) for noise reduction
- Side Tone function
 Internal VOX capability 200 memory channels with 8 character names
- · BNC type antenna connector





IP67 waterproofing



VHF AIR BAND TRANSCEIVER

SPECIFICATIONS

	IC-A16E	
GENERAL		
Frequency range	TX/RX : 118.000–136.992 MHz	
Number of memory channels	200 channels	
Channel spacing	8.33 kHz/25 kHz	
Type of emission	6K80A3E, 5K00A3E	
Power supply requirement	7.2 V DC	
Current drain (approximate)		
TX High	1.8 A	
RX Max. audio/Stand-by	650 mA/65 mA typical	
Antenna impedance	50 Ω (BNC type antenna connector)	
Operating temperature range	-20°C to +55°C	
Dimensions (W×H×D) (Projections not included)	52.2 × 111.8 × 34.1 mm (with BP-280)	
Weight (approximate)	257 g (with BP-280)	
TRANSMITTER		
Output power (at 7.2 V DC)	6.0 W (PEP), 1.8 W (carrier)	
Audio harmonic distortion	Less than 10% (at 85% + 3 dB modulation)	
Harmonics spurious emissions	Less than –36 dBm (Except for operating frequency ±1 MHz.)	
Frequency stability	±1 ppm	
RECEIVER		
Intermediate frequencies	46.35 MHz (1st), 450 kHz (2nd)	
Sensitivity	Less than 0 dBµ (at 12 dB SINAD with CCITT)	
Squelch sensitivity (Threshold)	Less than 0 dBµ	
Spurious response	More than 70 dB	
Hum and noise	More than 40 dB (at 90% modulation)	
	1500 mW typical More than 350 mW (AM 8 Ω 60% modulation at 10% distortion)	
	3 conductor 3.5 (d) mm	

All stated specifications are subject to change without notice or obligation.

Applicable U.S. Military Specifications

MIL 810G	
Method	Procedure
500.5	І, П
501.5	Ι, Π
502.5	І, П
503.5	I–C
505.5	Ι
506.5	I, III
507.5	II
509.5	_
510.5	Ι
512.5	Ι
514.6	Ι
516.6	I, IV
	Method 500.5 501.5 502.5 503.5 505.5 506.5 507.5 509.5 510.5 512.5 514.6

Ingress Protection Standard Dust and Water IP67/54

Supplied accessories : (* Not supplied, depending on the transceiver version.) BP-280 battery pack
 BC-213 rapid charger*
 BC-242 AC adapter* •FA-B02AR antenna •MB-133 belt clip •Hand strap

OPTIONS

BATTERY PACKS

BP-278	Rechargeable Li-ion 7.2 V
	1190 mAh (typ.), 1130 mAh (min.).
BP-279	Rechargeable Li-ion 7.2 V
	1570 mAh (typ.), 1485 mAh (min.).
BP-280	Rechargeable Li-ion 7.2 V
	2400 mAh(typ.), 2280 mAh (min.).
	Same as supplied.



▲BP-278 ▲ BP-279

DESKTOP CHARGER

MULTI-CHARGER

BC-213 Charges the BP-278, BP-279 or BP-280. BC-242 AC adapter. Same as supplied. BC-123SE/SUK/SV* AC adapter. * SE for Europe, SUK for UK, SV for Australia.



BC-214

OPC-515L For use with the BC-213. OPC-656 For use with the BC-214.

DC POWER CABLES

OPC-515L

HEADSET ADAPTER

SPEAKER-

OPC-2401

MICROPHONE HM-240 Waterproof BC-157S

OPC-656

BC-214* Charges up to six transceivers and/or batteries at the same time. BC-157S AC adapter.

* The AD-130 charger adapter is supplied with the BC-214, depending on the charger version

VEHICLE CHARGER CABLE CP-23L For use with the BC-213.



CHARGER BRACKET MB-130 For use with the BC-213.

Bluetooth[®] HEADSET VS-3 With side tone function when connected to transceiver.



BELT CLIP MB-133 Same as supplied. **BELT HANGERS** MB-96N Swivel type. MB-96F Fixed type. MB-96FL Longer type

> ▲MB-96N MB-96F

ANTENNA FA-B02AR Same as supplied.

SOFTWARE AND CABLE CS-A16 Programming software for Windows® PC. OPC-478UC USB type radio programming cable.

lcom, lcom lnc. and lcom logo are registered trademarks of lcom Incorporated (Japan) in Japan, the United States, the United Kingdom, Germany, France, Spain, Russia, Australia, New Zealand, and/or other countries. Windows is either a registered trademark or a trademark of Microsoft Corporation in the United States and/or other countries. The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by lcom Inc. is under license. All other trademarks are the properties of their respective holders.

ICOM Inc. 1-1-32, Kamiminami, Hirano-Ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013 www.icom.co.jp/world Count on us!

MB-96FL

Icom America Inc. www.icomamerica.com

Icom (Europe) GmbH www.icomeurope.com

Icom Canada www.icomcanada.com

Icom Brazil E-mail: sales@icombrazil.com Icom Spain S.L. www.icomspain.com

Icom (UK) Ltd. www.icomuk.co.uk

Icom France s.a.s. www.icom-france.com

Icom (Australia) Pty. Ltd. www.icom.net.au

Your local distributor/dealer:

Shanghai Icom Ltd. www.bjicom.com



IC-A16E